

הגדרת רשת WIFI בראוטר סלולרי

כניסה ללממשק ניהול:

מחברים את הראוטר לחשמל כאשר הוא עם סים ואנטנה מורכבים, בעזרת כבל רשת מתחברים למחשב, פותחים דפדפן וגולשים לכתובת 192.168.0.1

כניסה לממשק , USER: admin , Password: admin

הגדרה:

- SSID: הגדרת שם לרשת ה WIFI
- PSK PASSWORD: הגדרת סיסמה לרשת WIFI
- לסיום יש ללחוץ על SUBMIT ולאחר מכן על APPLY&SAVE

The screenshot shows the Robustel router's configuration interface. The 'WiFi' tab is selected. Under 'General Settings', the 'Enable' toggle is turned ON. The 'Wireless Mode' is set to '11bgn Mixed'. The 'Channel' is set to 'Auto'. The 'SSID' is set to 'Wilson'. The 'Broadcast SSID' toggle is turned ON. The 'Security Mode' is set to 'WPA-Personal'. The 'WPA Version' is set to 'Auto'. The 'Encryption' is set to 'Auto'. The 'PSK Password' field contains several dots. The 'Group Key Update Interval' is set to 3600. Arrows point to the SSID field (labeled 'שם הרשת'), the Security Mode dropdown (labeled 'סיסמה לרשת'), and the Submit button.

כדי לוודא שרשת ה WIFI הוגדרה ופועלת יש לעבור לחוצץ STATUS , שם צריך להופיע ב status , COMPLETED

The screenshot shows the 'AP Status' page in the Robustel router configuration interface. The 'Status' is 'COMPLETED'. The 'Channel' is '1'. The 'Channel Width' is '40 MHz'. The 'MAC Address' is '34:FA:40:08:4D:F0'. Below this is a table for 'Associated Stations' with columns for Index, MAC Address, IP Address, Name, Connected Time, and Signal.

Index	MAC Address	IP Address	Name	Connected Time	Signal
-------	-------------	------------	------	----------------	--------